WIAMI
HOME TECHNOLOGY

Akıllı Bluetooth Gözlük Kullanım Kılavuzu

Model: BG-02

Ürünümüzü tercih ettiğiniz için teşekkür ediyoruz. Cihazı kullanmaya başlamadan önce bu kılavuzu dikkatlice okumanız tavsiye edilir.

Özellikler

Çerçeve rengi: Siyah
Lens rengi: Siyah
Çerçeve materyali: Nylon,PC+ABS
Lens materyali: PC
Bluetooth versiyonu: 5.3
Şarj olma süresi: 1.5 Saat
Çağrı süresi: 10 Saat
Müzik çalma Süresi: 10 Saat
Bekleme süresi: 220 Saat
Batarya kapasitesi: 110mAh*2
Voltaj: DC 5V 110 mAh
Hoparlör türü: Çift (Stereo)

Kutu İçeriği

Gözlük
Şarj Kablosu
Temizleme Bezi
Kılıf
Kullanma Kılavuzu
Garanti Belgesi

Kullanım

Gözlüğün bacaklarını açtıktan sonra 5 saniye içerisinde cihaz otomatik olarak açılacaktır. Bluetooth eşleştirme moduna da otomatik olarak geçecektir.





Açma Kapama

Gözlüğün bacaklarını açtıktan 5 saniye sonra cihaz çalışmaya başlayacaktır. Gözlüğün bacaklarını kapattıktan 1 saniye sonra cihaz kapanacaktır.

Eğer cihazın bluetooth ile bağlı olmadığı süre 10 dakikayı geçerse cihazın bağlantısı kopacaktır.

Cihaz açıkken sağ ya da sol şakak tarafına 5 defa üst üste dokunursanız cihaz kapanır.

Bluetooth Eşleştirme

İlk defa eşleştirme yaparken cihaz otomatik olarak eşleştirme modunda çalışacaktır. Eşleştirme başarılı olduğuda uyarı bildirimi gelecektir.

Cihazın BT bağlantısı koparsa kontrol tuşuna önce üç kere basın ve dördün sefer basarken 5 saniye basılı tutun. Sıfırlama uyarısını duyacaksınız ve ışık 10 defa yanıp sönecek.

Cihaz BT ile eşleştirildiğinde ve bağlantısı koptuğunda uyarı bildirimi gelecektir.

Ses Ayarı

Sağ tarafa 2 saniyeden fazla basılı tutarsanız ses artacaktır. Sol Tarafa 2 saniyeden basılı tutarsanız ses azalacaktır.

Müzik Çalma

-Bir sonraki şarkı için sağ taraftaki tuşa 3 kere basın.
-Bir önceki şarkıya geri dönmek için sol taraftaki tuşa 3 kere basın.
-Müziği durdurup başlatmak için sağ ya da sol tarafta bulunan tuşa iki defa basın.

Çağrı Özellikleri

-Çağrı Cevaplama: Sağ ya da sol tuşa iki defa dokunun.
-Çağrı Sonlandırma: Sağ ya da sol tuşa iki defa dokunun.
-Çağrı Reddetme: Sağ ya da sol tuşa 1.5 saniye basılı tut.
-Birisiyle konuşurken başka birini çağrıya eklemek için sağ ya da sol tuşa basılı tutun. Çağrıyı sonladırmak için sağ ya da sol tuşa basılı tutun. ???
-Beklemede olan çağrıya dönmek için önce sağ ya da sol tuşa basarak o anki çağrıyı sonlandırın.

Sesli Komut

-Sağ ya da sol tarafa 4 defa basarak telefonunuzdaki sesli komut özelliğini devreye alabilirsiniz. (Farklı marka ve model telefonlara göre bu fonksiyon değişiklik gösterebilir ya da mevcut olmayabilir.)

Şarj

-Düşük şarj alarmı: 5 dakikada bir şarj az uyarısı verir. 14 saniyede bir ışık yanıp söner.
-Düşük şarj sebepli kapatma: Ses çalacaktır ve ışık 5 saniye yanar.
-Şarj olurken ışık yanıp söner. Şarj olma işlemi bittiğinde devamlı yanar.
-Cihaz şarj olurken ortam sıcaklığı 0-45℃ arasında olmalıdır.

Önemli Kullanım Bilgileri

-Cihazı kullanmadan önce bu kılavuzu dikkatlice okuyunuz ve kılavuzu kaybetmeyiniz.
-Cihazı kullanmaya başlamadan önce batarya tam dolana kadar şarj ediniz.
-Cihazı iki hafta boyunca hiç kullanmadıysanız, tekrar kullanmaya başlamadan önce şarj ediniz.
-Lensleri doğrudan silmeyiniz. Öncelikle lensleri biraz ıslatın. Ardından kadife bir temizleme bezi ve emici gözlük temizleme bezi kullanarak nazikçe temizleyin. Silerken ileri geri ya da yuvarlak biçimde silme hareketi yapmayın. tek bir yöne doğru silme işlemi gerçekleştirin.

Uyarılar

-Cihazı kullanmadan önce uyarıları okumanız cihazı güvenli şekilde kullanmanız için önemlidir.
-Sadece üretici tarafından onaylanmış bir şarj kablosu kullanmanız önerilir. Aksi takdirde yanma, patlama ya da başka kazalar olabilir.
-Cihaz yanma sebepli ya da elektronik bir hasar alırsa, cihaza tamir amaçlı müdahale etmeyin. Resmi teknik servis ile iletişime geçin.
-Cihazı sadece 0-35 °C arası ortamlarda kullanmalısınız. Cihazı -20 ile +45 °C olan ortamlarda saklayabilirsiniz.
-Şarj dolumu tamamlandığında kabloyu cihazdan ayırınız. 12 saatten uzun süre cihazı şarjda bırakmayın.
-Cihaz ev artıkları ile beraber çöpe atılmamalıdır. Bu durum çöpte bataryadan çıkabilecek yangınlara sebep olabilir. -Cihaz ateşe maruz bırakılmamalı ve ateş içine atılmamalıdır
-Bu cihazda yerinden çıkartılmayan, gömülü bir batarya mevcuttur. Bu bataryaya müdahele edilmemeli, yerinden sökülmemeli ve açıkta bırakılmamalıdır. Bataryada şişme varsa kullanımı durdurulmalı ve resmi teknik servis ile iletişime geçilmelidir.
-Cihazda manyetik bileşenler bulunmaktadır (gözlük bacakları ve manyetik şarj kısmı). Bu kısımları metal eşyalardan uzak tutarak kısa devre riskini azaltabilirsiniz. Kısa devre yaşanması durumunda cihaz aşırı ısınabilir ve derinize zarar verebilir.
-Cihaz uzun süre güneş ışığına maruz bırakılmamalıdır. Aksi takdirde korozyona ve deformasyona uğrayabilir.
-Cihazı benzin istasyonları ya da depoları, kimsyasal depolar gibi yanıcı maddelerin olduğu ortamlarda kullanmayınız.
-Cihazı hastaneler ve acil müdahale merkezleri gibi manyetik alet bulunduran ortamlarda interferansa sebep verebileceği için kullanmayınız. Kalp pili, duymaya yardımcı cihazlar ve diğer cihaz ya da implantlardan uzak tutunuz.
-Cihazı medikal aletler etrafında kullanacaksanız doktorunuza danışınız.
-Cihazı yıldırımlı havalarda kullanmaktan kaçınınız.
-Elektrik çarpmasına ve yangınlara sebep olmamak için şarj aletini aşırı nemli ortamlarda (tuvalet gibi) kullanmayınız.
-Uzun süre boyunca en yüksek seviyede müzik dinlemeniz tavsiye edilmez.

Hızlı Kullanım Bilgileri

Fonksiyon	Aksiyon	Bildirim
Cihazı Açma	Gözlük Bacaklarını Aç	Açıldı Bildirimi
Cihazı Kapatma	Gözlük Bacaklarını Kapat	Kapandı Bildirimi
Çağrı Kabul Etme	Sağ/Sol Tuşa 2 Defa Bas	
Çağrı Bitirme	Sağ/Sol Tuşa 2 Defa Bas	
Çağrı Reddetme	Sağ/Sol Tuşa 1.5 saniye uzun bas	
Başlat/Durdur	Sağ/Sol Tuşa 2 Defa Bas	
Sesi Artır	Sağ Tuşa 2 saniye basılı tut	
Sesi Azalt	SolTuşa 2 saniye basılı tut	
Önceki Şarkı	SolTuşa 3 defa bas	
Sonraki Şarkı	4 defa bas	
Sesli Asistan	3 defa bas ve basılı tut	
Eşleştirmeyi Boz	4 defa bas ve basılı tut	Sıfırlama Bildirimi
Şarj Etme	-	Işık Devamlı Yanıp Söner
Şarjın Tamamlanması	-	Işık Kalıcı Şekilde Yanar

Cihazda Bulunan Zararlı Materyaller Tablosu

Parça İsmi	Zararlı Materyaller					
	(Pb)	(Hg)	(Cd)	(Cr6+)	(PBB)	(PBDE)
Devre Kartı	×	○	○	○	○	○
Plastik	○	○	○	○	○	○
Metal	×	○	○	○	○	○
Batarya	×	○	○	○	○	○
Kasa	×	○	○	○	○	○

Bu form SJ/T 11364 provizyonlarına uygun olacak şekilde hazırlanmıştır.

O: Zararlı maddelerin içeriği, parçada bulunan bileşenlerin tümünde, GB/T 26572'de belirtilen limitlerin altında anlamına gelir.
X: Zararlı maddelerin içeriği, parçada bulunan bileşenlerin en az bir tanesinde, GB/T 26572'de belirtilen limitlerin üzerinde anlamına gelir.

Bu ürünün çevre koruma kullanım süresi 10 yıldır. Piller gibi değiştirilebilir parçaların çevre koruma kullanım süresi, ürünlerin çevre koruma kullanım süresinden farklı olabilir. Çevre koruma kullanım süresi, yalnızca ürün bu kılavuzda açıklanan normal koşullar altında kullanıldığında geçerli olacaktır.

SHENZHEN GEEKORS TECHNOLOGY LIMITED

Original Declaration of Conformity

WIAMI
HOME TECHNOLOGY

EU DECLARATION OF CONFORMITY

Apparatus/equipment
Product: Smart Audio glasses
Model: BG-02
BAU No:
Batch or Serial Number:

Manufacturer or his authorized representative:
Name: SHENZHEN GEEKORS TECHNOLOGY LIMITED
Address: 7F, C Block, White Deer Plaza , No. 48 Gonghe Industrial Road, Bao'an District, Shenzhen City, Guangdong Province, CHINA
Country: China

Manufacturers authorized EU Representative
Name:
Address:
Country:

This declaration of conformity is issued under the sole responsibility of the manufacturer.

Object of the declaration: Listed above

References to the relevant harmonized standards used , including the date of the standard, or references to the other technical specifications, including the date of the specification, in relation to which conformity is declared:

Harmonized Standard	Test lab
EN 55032:2015+A1:2020 EN 55035:2017+A11:2020 EN IEC 61000-3-2:2019+A1:2021 EN 61000-3-3:2013+A1:2019	Shenzhen Microtest Co., Ltd
EN IEC 62368- 1:2020+A11:2020	Shenzhen Microtest Co., Ltd
EN 300 328 V2.2.2 : 2019	Shenzhen Microtest Co., Ltd
ETSI EN 300 328 V2.2.2 : 2019	Shenzhen Microtest Co., Ltd
EN 301 489- 1 V2.2.3 :2019 EN 301 489- 17 V3.2.4: 2020	Shenzhen Microtest Co., Ltd
EN 62479:2010 EN 50663:2017	Shenzhen Microtest Co., Ltd

Notified Body (Optional) :
Name of notified body:
Reference Number of the certificate:
4 digit notified body number:

Signed for and on behalf of
Place and date of issue: March , 8 , 202 3

SHENZHEN GEEKORS TECHNOLOGY LIMITED
7F, C Block, White Deer Plaza , No. 48 Gonghe Industrial Road, Bao'an District, Shenzhen City, Guangdong Province, CHINA 518147

Signature:

Name, function: Arthur Ouyang , Compliance Engineer

Color Image of product:

User's Manual

Instruction

Great thanks for using our products! Please read this manual before using the product. The contents of the manual are subject to modifications for better service. Modifications due to changes of performance and functionality of the product if needed is without prior notification.

Product Model:BG-02

Product Name: Smart Audio Glasses

This product, easy to operate and practical, is a portable bluetooth glasses with stereo sound and an elegant appearance.l.

Designed and manufactured in China.

I. Product Parameter:

1. Frame color: black
   Lens color: black
2. Frame material: Nylon,PC+ABS
   Lens material: PC
3. Bluetooth version: 5.3
   Charging time: 1.5 hours
5. Call duration: 10 hours
6. Music playback: 10 hours
7. Standby: 220 hours
8. Battery capacity: 110mAh*2
9. Charging current: DC5V,110mA
10. Channel: dual speakers, stereo

II. Packing List:

Glasses*1;
Charging cable*1;
Glasses cloth*1;
Glasses case*1;
Manual*1;
Warranty card*1.

III. Operations:

Tips: To quickly find the touch button, use your finger to slide from the middle of the glasses legs to the front until touch the button. At this time, A finger off counted as a click operation.

Separating the legs of the glasses to awake the device, within 5 seconds the left and right leg of the glasses will automatically matching up. Enters Bluetooth connection mode, which allows you to find Bluetooth devices and complete the connection.





On/Off

1.Separating the legs of the glasses to awake the device, prompt "ringtone", the indicator light will be on for 1 seconds.

2. Closing the legs of the glasses to shut down the device, prompt "ringtone" indicator light lasts for 1 second.

3. Disconnected to the phone for 10 minutes, the product will automatically power off, prompt "ringtone".

4. In the power-on state, click the left or right temples 5 times in a row, and the left and right temples will be turned off at the same time, and the prompt "ringtone".

Bluetooth Pairing Connection

1. For the first pairing, the left and right temples will be automatically paired within 5 seconds after the power is turned on and the indicator light flashes quickly.
2. When the phone is not connected, click the button 4 times (long press for about 5 seconds for the fourth time) to clear the pairing record, and the indicator light flashes 10 times.
3. The prompt sound "Device Connected" after connecting with the mobile phone; when the connection with the mobile phone is disconnected, the prompt sound "Device Disconnected".

Volume Control

Right click + long press for more than two seconds to increase the volume

Left click + long press for more than two seconds to decrease the volume

Play Music

1. For the next song, triple-click the right button.
2. For the previous song, three-click the left button.
3.Music pause/play, double-click the left/right button.

Call Functions

1.Provide different tones for different brands and models of mobile phone devices in call reminder service.
2. Answer the call Double-click the left/right button.
3. Hang up the call, double-click the left/right button.
4. To reject the call, press and hold the left/right button for more than 1.5 seconds.
5. While on the phone, hold click the left or right to add-on the Third Party while holding the call;

Hold click the left or right button to end the call and accept the third-party call.

6. In a three-way call, hold click the left or right button to end the current call and get through the previous held call;

Voice Assistant

Four clicks on the left or right temple button can wake up the phone assistant and realize voice interaction.(Need the support of the mobile phone system, different brands and models of mobile devices, assistant functions are different).

Charging

1. Low battery alarm, prompting once every 5 minutes "Batterylow" indicator flashes once every 14 seconds.

2. Low power shutdown, prompt "ringtone", indicator light lasts for 5 seconds.

3. When charging, the indicator light flashes.The indicator light is always on when charging completed.

4. Use mobile phone to check the batter power of the glasses (Backup by mobile phone)

Other

Charging temperature range should not exceed 0-45℃

IV. Prompts

1. Please read the instruction manual thoroughly before using the product. Always include and keep this safety guide.

2. Fully charged before the first use.

3.When not using the battery pack for extended periods of time(every 2 weeks), please charge before using

(4) Do not wipe the lens directly, wet the lens first and then use velvet and absorbent eyeglass cloth wiping in the same direction gently. Wiping back and forth or in circular is not suggested.

V. Warnings:

1.Before using, read all the safety information to ensure proper and safe operation.

2.Only use a charging cable recommended by the manufacturer or otherwise may cause fire, explosion or other accidents.

3.In case of fire, electronic damage or even complete scrap of the product, please do not dismantle or refit the product for any reason.

4. Only use the product at ambient temperature between 0℃～35℃ and keep the product as well as the accessories at temperature between -20℃～45℃ for temperature too low or too high may cause functional faults.

5.When charging completed, disconnect the charger from the product and the charger from the socket. Do not exceed 12 hours of continuous charging time.

6. Always keep the product dry.

7. The product must not be disposed with normal household waste to avoid battery fire or explosion. For packing disposal, please observe the legal regulations in your country.

8. This product is with a built-in-non-removable lithium battery, which must not be disassembled, bumped, squeezed or exposed to fire. For any serious expansion of batteries, please stop using.

9. Maintain a distance between the product components containing the magnet (the glasses legs and the charging cable) and metal objects to avoid danger of electrical short-circuit which will lead to the overheating of the battery and cause personal injuries such as skin burns.

10. The product must not be exposed to or thrown into fire to avoid explosion.

11. Do not expose the product to sunlight for a long time to avoid corrosion or deformation.

12. Only use the product complying with the relevant laws and regulations, and do not use in the following environments.

● Do not use the product in the vicinity of gas stations, oil depots, chemical warehouses, etc., where flammable or explosive gas or chemicals are stored.

● Do not use this equipment in hospital operating rooms, emergency rooms, intensive care units, etc for the magnetic fields could cause interference with cardiac pacemakers implanted defibrillators (ICDs), hearing-aid, cochlear and other implants. Always keep a at least 15-Centermeter distance to the peacemaker.

● Please consult your physician and the device manufacturer if you want to use this device near personal medical equipment.

● Please do not use the product in an environment that requires special attention such as in traffic, driving.

● Do not use the product outdoors during thunderstorms to avoid lightning strikes.

● Do not use the charger in a high humidity area such as a bathroom, as electric shock, personal injury, fire and the charger damage may result.

● Please comply with any legal requirements that expressly prohibit the use of the product in any environment.

Quick Guide

Instruction	Operation	Prompt
On	Separate Spectacle Legs	Power On
Off	Close Spectacle Legs	Power Off
Accept Call	Double- Click The Left/Right Button	
End Call	Double- Click The Left/Right Button	
Reject Call	Long press left/right key for more than 1.5 seconds	
Play/Pause	Double- Click The Left/Right Button	
Volume +	Right click+long press more for 2 seconds	
Volume -	Left click+long press more for 2 seconds	
Last Song	Triple-click The Left Button	
Next Song	Four strikes	
Voice Assistant	Three click +long press more for 5 seconds	
Clear Pairing	Quadruple-click And Long-pressing	Reset
Charging	-	Indicator breathing
Fully Charged	-	The indicator is always on

Name and content of harmful substances in products

Part Name	harmful materials					
	(Pb)	(Hg)	(Cd)	(Cr6+)	(PBB)	(PBDE)
Circuit board assembly	×	○	○	○	○	○
Plastic	○	○	○	○	○	○
Metal	×	○	○	○	○	○
Battery	×	○	○	○	○	○
Enclosure	×	○	○	○	○	○

This form is prepared in accordance with the provisions of SJ/T 11364

O: It means that the content of the hazardous substance in all homogeneous materials of this part is below the limit requirements stipulated in GB/T 26572.

X: It means that the content of the hazardous substance in at least one homogeneous material of the part exceeds the limit requirements stipulated in GB/T 26572.。

The environmental protection use period of this product is 10 years, and the logo is shown on the left. The environmental protection use period of replaceable parts such as batteries may be different from the environmental protection use period of products. The environmental protection use period will only take effect when the product is used under the normal conditions described in this manual.